

## DLC 5.1 Premium UFO High Bay - HB07 Series

UFO High Bay Light (HB07 series) is widely used in the warehouses, gymnasiums and production assembly areas.



Lower UGR<27

High Efficacy to 140LM/W

UL/cUL, DLC 5.1 Premium Listed

120-277VAC available



## PRODUCT APPEARANCE




## PRODUCT SPECIFICATION


| Product No. | HB07-100W-X-YY | HB07-150W-X-YY | HB07-200W-X-YY | HB07-240W-X-YY |
|-------------|----------------|----------------|----------------|----------------|
| Wattage     | 100W           | 150W           | 200W           | 240W           |
| Lumens      | 14000lm        | 21000lm        | 28000lm        | 33600lm        |

|               |  |                     |  |
|---------------|--|---------------------|--|
| Efficacy      | 140LM/W (±5%)                                    | Frequency           | 50/60Hz  |
| Input voltage | 120-277VAC                                       | Lens Material       | UV Stabilized Polycarbonate                        |
| CCT           | 3000-6500K                                       | Housing             | Die-cast Aluminum                                  |
| THD           | <20%   | CRI                 | Ra>80  |
| LED Type      | 2835   | Finish              | Black/Grey/White/ Customized (Optional)            |
| Beam Angle    | 90° for all wattages,<br>120° for 150W 200W 240W | Additional function | Plug-in Sharkward / Haisen Microwave Motion Sensor |
| IP Rating     | IP65   | Life Time           | >50,000Hrs   |
| Power Factor  | ≥0.95  | Warranty            | 5 Years  |
| IK Degree     | IK10   | Certificates        | UL/cUL, DLC 5.1 Premium                            |


## PRODUCT DIMENSION



100W



150W



200W/240W

## INSTALLATION INSTRUCTION

### Ceiling with Loop

1. Fix the luminaire with a chain to the ceiling;
2. Use the buckles to fix safety rope with the body and loop;
3. Connect the wires.




### Pendant Mounting

1. Fix the luminaire with bar and tighten the pole with an anti-skid screw;
2. Use the buckles to fix the safety rope with the lampbody and ceiling;
3. Connect the wires.



### Ceiling with Hook

1. Unscrew the hook, fix the luminaire to the installation holders and screw the hook tightly;
2. Use the buckles to fix the safety rope with the body and hook;
3. Connect the wires.



### Wall Mounting

1. Trepan the installation holes as the size of the following figure;
2. Use M 10 screws to tighten the luminaire. The holder can be adjusted from 60D to 120D;
3. Use the buckles to fix the safety rope with the body and loop;
4. Connect the wires.



## ADDITION ACCESSORIES



PC Reflector



Aluminum Reflector



Safe Rope



Emergency Driver

Sharkward Plug-in  
Microwave Motion SensorSharkward Screw-in Zhaga  
Microwave Motion SensorHaisen Screw-in Zhaga  
Microwave Motion Sensor

## MOUNTING OPTION



Ceiling with loop



Ceiling with hook



Wall mounting



Pendant mounting

## PACKING INFO

| Model No.      | Product Dimension<br>(mm&inch) | Carton Size<br>(mm&inch)               | Net Weight<br>(KG) | Gross Weight<br>(KG) | 20GP | 40GP | 40HQ |
|----------------|--------------------------------|--|--------------------|----------------------|------|------|------|
| HB07-100W-X-YY | Ø256X164.5<br>(Ø10.1"X6.5")    | 290*290*150mm<br>(11.42"*11.42"*5.91") | 1.8                | 2.34                 | 1944 | 3888 | 4722 |
| HB07-150W-X-YY | Ø290X164.5<br>(Ø11.4"X6.5")    | 320*320*155mm<br>(12.6"*12.6"*6.11")   | 2.13               | 2.73                 | 1558 | 3116 | 3784 |
| HB07-200W-X-YY | Ø332X176.7<br>(Ø13.1"X7.0")    | 360*360*165mm<br>(14.17"*14.17"*6.50") | 2.89               | 3.77                 | 1168 | 2337 | 2838 |
| HB07-240W-X-YY | Ø332X176.7<br>(Ø13.1"X7.0")    | 360*360*165mm<br>(14.17"*14.17"*6.50") | 3.19               | 4.07                 | 1168 | 2337 | 2838 |